




NETVOX G100

4 LINE ALPHANUMERIC FLEXTM PAGER

Function Buttons



Message Icons







Road Message or Old Message Indicate

Mossage Protection Released Indicaret

Message Dekard Industor

Alert Settings

- Press to enter the function menu screen from the status screen
- Press f or ,, to move through function menu icons until audible alert, silent alert (vibrate) or silent beep (vibrate and beep) appears
- Audible alert; press \neg to enter alert options. Use f or " to scroll through alert options. Press ¬ to select alert.
- Silent alert/silent beep; press ¬ to confirm alert

Thank you for choosing the NETVOX G100.

Tomvic Industries Ltd

Authorised Distributor of Netvox Pagers PO Box 34634 13 Sunnyhaven Ave Beach Haven Village Auckland Ph: (09) 481 9020

Fax: (09) 481 9029 Email: info@tomvic.co.nz Web: www.tomvic.co.nz

Pager On:

Place one AAA alkaline battery into back of pager. Pager will alert. Press - to stop alert.

Pager Off:

- Press button
- Select 'turn pager off' using f or "
- Press button to turn pager off
- Press and hold to turn pager back on

Time and date

- Press to enter function menu screen from the status screen
- Press f or ,, to move to 'set time/date'
- Press ¬ to enter 'set time/date' option
- Press " to move through hours/minutes and date
- Press f to adjust settings
- Press to confirm setting

Getting Started

Pager Features:

- 4 line, 20 characters per line
- Up to 30 personal message slots
- Notebook stores up to 99 messages
- 5 alarm clocks
- Silent beep, vibrate and 26 user selectable alerts
- GPS Update time and date updated by network
- Auto on/off at selectable times
- Backlight

Status Screen:



- Number of Personal Messages
 - Signal Indicator Coverage Indicator
 - Alert Mode Indicator
 - Low Battery Alert
- N/A in NZ Alarm Indicator
- Automatic On / Off Indicator
- Time Display
- Continuous Message Indicator
- Day of Week Indicator

Function Menu

- Press to enter the function menu screen from the status screen
- Press f or ,, to move through function menu icons
- Press ¬ to enter the current selected function sub-menu (function setting mode)

Alarm Setting (5 alarms)

- Press to enter function menu screen from the status screen
- Press f or ... to move to 'set alarm'
- Press ¬ to enter 'set alarm' option
- Press again to change settings
- Use \mathbf{r} to move through hours/minutes and \mathbf{f} to change setting
- Press ¬ to confirm alarm setting/s

Reading a message

When a message is received your pager will alert. Press ¬ to read the new message.

f message is longer than one screen press - until message is read.

Press f or f or f to skip through messages.

Set Auto On/Off Function

- Press to enter the function menu screen from the status screen
- Press f or ,, to move to 'set auto on/off'
- Press ¬ to enter 'set auto on/off' option
- Use " to move through hours/minutes
- Press **f** to change setting

3 On

Press ¬ to confirm setting

Ø Off Backlight

- Press and ¬ buttons at the same time to turn on backlight
- Repeat the same steps to turn backlight off

Saving a Message

When 30 messages have been received in the Personal Message Area the next personal message will overwrite the oldest message. Therefore, it is important to save messages that you do not want to be overwritten.

- Display message on the screen
- Press to enter the message function menu
- Press f or " to move to 'protect message'
- Press ¬ to confirm

Repeat steps above to unprotect message. Choose 'unprotect message' from the message function menu.

Deleting a Message or All Messages

- Display message on the screen
- Press to enter the message function menu
- Press f or \cdot to move to 'delete message'/'delete all'
- Press ¬ to confirm

Group Messaging Function (this function separates group messages from the personal message area. The function has to be programmed into the pager - contact your Dealer or Tomvic Industries Ltd)

- Press to enter the function menu screen from the status screen
- Press f or ,, to move to 'mailbox'
- Press ¬ to enter mailbox area
- Press f or π to select mailbox
- Press ¬ to read mailbox message
- Press f or ,, to select message within mailbox

Saving a Message in Notebook Area

- Display message on screen
- Press to enter the message function menu
- Press f or u to move to 'save to note'
- Press to confirm

To Read Message in Notebook Area

- Press to enter the function menu screen from the status screen
- Press f or \cdot to move to 'personal note'
- Press ¬ to read messages
- Press f or \cdot to move through messages

To install or replace battery

- Place the pager face down in the palm of your hand
- Release sliding latch and push sideways with a click to unlock the battery cover, slide battery cover along and out
- When replacing batteries turn pager off, remove old battery and replace with new battery. Check polarity is correct
- Place cover on track and move along until cover clicks in place. Push down sliding latch.

ALWAYS USE AN ALKALINE BATTERY

Service and Repair

Complete the warranty form enclosed in pager box.

Contact your Paging Dealer or Tomvic Industries Ltd for enquiries for servicing your pager.

TOMVIC INDUSTRIES LTD

PO Box 34634 Birkenhead Auckland New Zealand Ph: (09) 481 9020 Fax: (09) 481 9029 info@tomvic.co.nz www.tomvic.co.nz

Netvox G100 Paging Accessories

Give your pager added protection and security with the range of PagerMate® accessories.



A large selection of pager pouches are available. These all provide added protection for the pager screen and are splash proof.

For added security PagerMate® has a large range of chains and bungee cords to ensure you won't loose your pager while on the move.



PagerMate® Wireless Messaging Software

PagerMate® has a range of software available to suit all your business needs from standalone PCs to larger server environments. The software is reliable, feature-rich and designed for end users who require alphanumeric (text) paging capabilities from a PC or Laptop. The software enables you to send messages to text enabled mobile phones as well as pagers, providing you with an efficient and effective way of communicating to people on the move.

- Wireless Office Express Entry Level Software
- Wireless Office Ability to schedule future messages
- Wireless Pro Selectively forward emails to pagers or phones
- WordTrek Plus Portable unit with built in modem & software

Server software available upon request. Distributed by Tomvic Industries Ltd.